HS-100F Accelerometer

AC acceleration output via 2 Pin MS Connector


Key Features

- Most common seller
- · For use with data collector
- Customisable features



Building services, Pulp and Paper, Mining, Metals, Utilities, Automotive, Water, Pharmaceutical, Wind





Connection Details



| Technical Pe | erformance |
|--------------|------------|
|--------------|------------|

| Mounted Base Resonance | see 'How To Order' table (nominal) |
|------------------------|--|
| Sensitivity | see: 'How To Order' table ±10% |
| | Nominal 80Hz at 72°F |
| Frequency Response | 90cpm (1.5Hz) to 600kcpm (10kHz) ± 5% |
| | 30cpm (0.5Hz) to 720kcpm (12kHz) ± 10% |
| | 12cpm (0.2Hz) to 900kcpm (15kHz) ± 3dB |
| Isolation | Base isolated |
| Range | see: 'How To Order' table |
| Transverse Sensitivity | Less than 5% |
| | |

| Case Material | Stainless Steel |
|------------------------------|--|
| Sensing Element/Construction | PZT/Compression |
| Mounting Torque | 5.9ft. lbs |
| Weight | 3.7 oz. (nominal) body only |
| Sheilded Cable Assembly | see: www.hansfordsensors.com for options |
| Connector | HS-AA004 - non-booted |
| | HS-AA053 or HS-AA054 - booted |
| Mounting Threads | see: 'How To Order' table |
| | |

| Electrical | |
|--------------------|------------------------------------|
| Excitation Voltage | 18-30Volts DC |
| Electrical Noise | 0.1mg max |
| Current Range | 0.5mA to 8mA |
| Bias Voltage | 10 - 12 Volts DC |
| Settling Time | 2 seconds |
| Output Impedance | 200 Ohms max. |
| Case Isolation | >10 ⁸ Ohms at 500 Volts |


Environmental

Mechanical

| Operating Temperature Range | |
|-----------------------------|--|
| Sealing | |
| Maximum Shock | |
| EMC | |

| -67 | to | 284°F |
|--------|-----|--------|
| | | IP68 |
| | | 5000g |
| EN6132 | 6-1 | 1.2013 |

Typical Frequency Response (at 100mV/g)



Applications

Fans, Motors, Pumps, Compressors, Centrifuges, Conveyors, Air Handlers, Gearboxes, Rolls, Dryers, Presses, Cooling, VAC, Spindles, Machine Tooling, Process Equipment

Vibration sensor should be firmly fixed to a flat surface (spot face surface may be needed to be produced and cable anchored to sensor body.)



How To Order

| | uct Series Industrial Vibration Ser | sor | | |
|---|---|--|--|---|
| H S 1 0 | 0 F | x x x x | x x x | |
| Extra Options (if required) F - Filtered I - Intrinsically Safe L - 316L Stainless Steel RT - Temperature Output PT100 T - Temperature Output Y - 5% tolerance on sensitivity | 010 - 10mV/g 030 - 30mV/g | tange Resonant Frequency 800g 1,680kcpm (28kHz) 250g 1,560kcpm (26kHz) 160g 1,440kcpm (24kHz) ±80g 1,320kcpm (22kHz) ±32g 1,200kcpm (20kHz) ±16q 1,080kcpm (18kHz) | Cable/Connector 01 - PUR 02 - Braided 07 - Silicon 08 - Flame Retardant 50 - 2 Pin MS 54 - M12 | Mounting Thr 01 - ¼-28" UN 02 - ¼-28" UN 05 - Quick Fit 06 - M6 x 1mn 08 - M8 x 1.25 10 - M10 x 1.5 |



www.hansfordsensors.com sales@hansfordsensors.com



We reserve the right to alter the specification of this product without prior notice \$\$T\$124U.8\$